



238 Pillow Street
 Butler, PA 16001
 724-283-4681
 724-283-5939 (fax)
 www.bwieagle.com

PRODUCT INFORMATION BULLETIN

AIR-EAGLE® GOLD PLUS 900 MHz RF Transmitter DUAL CONTACT INPUT MODEL 48-1000-12VDC

New and Improved Performance!

The Air-Eagle Gold Plus provides the same protection as the original Air-Eagle Gold but with enhanced output power. This allows for a 50% increase in overall range, while improving signal strength through and around buildings and other obstacles. These combine to maintain an even stronger "link" between transmitter and receiver.

DESCRIPTION

The AIR-EAGLE GOLD PLUS RADIO REMOTE TX IS a dual contact input transmitter designed to transmit a unique signal to the AIR-EAGLE GOLD 900MHZ RECEIVER. This model comes equipped with a terminal strip for ease of interfacing with any external **dry contact input** devices such as tilt switches, flow switches, speed switches etc.

PC BOARD SET-UP INFORMATION

Make the following connections on the PC Board Terminal Strip:


DC INPUT TERMINAL STRIP (DC IN)	
Terminal 1	Positive (+) 12VDC INPUT
Terminal 2	Negative (-) 12VDC INPUT

INPUT 1 TERMINAL STRIP (INP1)	
Terminal 1	CH1 Dry Contact Input (+)
Terminal 2	CH1 Dry Contact Input (Common)
Terminal 3	CH2 Dry Contact Input (Common)
Terminal 4	CH2 Dry Contact Input (+)

I/O TERMINAL STRIP (TERM2)	
Terminal 1	Not Used On This Model
Terminal 2	Not Used On This Model

NETWORK SWITCH TERMINAL STRIP (NSW1)	
Terminal 1	Not Used On This Model
Terminal 2	Not Used On This Model

NETWORK SWITCH CONFIGURATION OPTIONS (SEL1)		
SW #	OPEN	CLOSED
SW1	Not Used	Not Used
SW2	Not Used	Not Used
SW3	Not Used	Not Used
SW4	Not Used	Not Used




AIR-EAGLE® GOLD PLUS

900 MHz RF Transmitter
DUAL CONTACT INPUT

MODEL 48-1000-12VDC

DIMENSIONS & INDICATORS



CH1 LED - RED LED illuminates continuously while the CH1 contacts are closed.

LINKED LED - GREEN LED is illuminated while the transmitter is linked with the receiver.

CH2 LED - RED LED illuminates continuously while the CH2 contacts are closed.

SPECIFICATIONS

Power Supply	External 12VDC
Fuse Protected	2 amp
Transmit Frequency	900 MHz - 74 Channel Auto-Select
RF Output Power	1W
Transmit Range	Up to 10 miles with external antenna - see accessories)
Enclosure	Fiberglass NEMA 4, 4x, 12 + 13

REPLACEMENT PARTS & ACCESSORIES

PC Board (Main)	48-1002-12VDC
Air-Eagle Gold Plus Receiver	48-5000
Replacement Transceiver Antennas:	
900 MHz Omni Directional Antenna Medium Range Operation – For Ranges Up to 2 miles *	49-3101
900 MHz 13.9 dB Yagi Antenna Long Range Operation - External (Greater than 2 miles / Up to 10 miles) *	49-3102
Inline Lightning Arrestor	49-5002
* = Line of Sight	

LIMITED WARRANTY STATEMENT

BWI Eagle Inc. warrants the Air-Eagle Remote Control System, if properly used and installed, will be free from defects in material and workmanship for a period of **1 year** after date of purchase. Said warranty to include the repair or replacement of defective equipment. This warranty does not cover damage due to external causes, including accident, problems with electrical power, usage not in accordance with product instructions, misuse, neglect, alteration, repair, improper installation, or improper testing. This limited warranty, and any implied warranties that may exist under state law, apply only to the original purchaser of the equipment, and last only for as long as such purchaser continues to own the equipment. This warranty replaces all other warranties, express or implied including, but not limited to, the implied warranties or merchantability and fitness for a particular purpose. BWI Eagle makes no express warranties beyond those stated here. BWI disclaims without limitation, implied warranties of merchantability and fitness for a particular purpose. Some jurisdictions do not allow the exclusion of implied warranties so this limitation may not apply to you. To obtain warranty service, contact BWI Eagle for a return material authorization. When returning equipment to BWI Eagle, the customer assumes the risk of damage or loss during shipping and is responsible for the shipping costs incurred.

DOCUMENT DATE: 23-Feb-05



238 Pillow Street
Butler, PA 16001
(724) 283-4681
Fax (724) 283-5939
www.bwieagle.com